

Date

Name

Client



Project Name


Quote#

Type/Quantity

DIRO TRIMLESS OK LED 2733-9
202 145 81922

[Weblink](#)



Cutout shape/size:  Ø KIT mm

Recessed depth (mm): 105 mm

Available colors: BLACK (202 145 81922 B)
 WHITE (202 145 81922 W)
 GOLD MAT (202 145 81922 MMAT)

ADJUSTABLE 0-30° / 355°
 INCL.1 x POWERLED WHITE 6,2-9,3W / CRI>90 / 2700K / max.939lm
 INCL.1 x REFLECTOR FL-33°
 EXCL.LED POWER SUPPLY 350-500mA-DC

LED Technics: Light source: 939 lm // 9 W // 104 lm/W
 Luminaire: 11 W

Class: III

Weight: 0.3 KG

Protection level: IP20

Minimum distance: n.a.


Options: LED POWER SUPPLY 350 / 500mA-DC DIM

Requirements: MOUNTING KIT R82 TRIMLESS O.F.A.

For detailed installation instructions, please consult the manual. [202_145_81XXX_HAND.pdf](#)

DIRO TRIMLESS OK LED 2733-9
202 145 81922


Ceiling compatibility



System ceiling

Only with


[MOUNTING KIT R82](#)
[TRIMLESS O.F.A.](#)



Plasterboard

Only with


[MOUNTING KIT R82](#)
[TRIMLESS O.F.A.](#)



Stucanet

Only with

[MOUNTING KIT R82](#)
[TRIMLESS O.F.A.](#)



Concrete + plaster

Only with

[MOUNTING KIT R82](#)
[TRIMLESS O.F.A.](#)

DIRO TRIMLESS OK LED 2733-9
202 145 81922

Related references

LED POWER SUPPLIES

[Weblink / Specsheet](#)

LED POWER CONVERTOR 24V-DC TO 350mA / 15W
 300 2415 350
 Number of luminaires: 2

[Weblink / Specsheet](#)

LED POWER CONVERTOR 24V-DC TO MULTI CURRENT 48W DIM9
 300 90 67
 Number of luminaires: 2 / - / -


[Weblink / Specsheet](#)

LED POWER SUPPLY 350mA-DC / 10W DIM8
 300 90 110
 220-240V / 50-60Hz
 Number of luminaires: 1

[Weblink / Specsheet](#)


LED POWER SUPPLY 350mA-DC / 15W
 300 90 91
 110-240V / 50-60Hz
 Number of luminaires: 2(1)

[Weblink / Specs sheet](#)




LED POWER SUPPLY 350mA-DC / 16W DIM8
300 90 3112
110-240V / 50-60Hz
Number of luminaires: 2-2

[Weblink / Specs sheet](#)




LED POWER SUPPLY 350mA-DC / 17W
300 90 913
110-240V / 50-60Hz
Number of luminaires: 2(1)

[Weblink / Specs sheet](#)




LED POWER SUPPLY 350mA-DC / 18W DIM8
300 90 116
220-240V / 50-60Hz
Number of luminaires: 2-2

[Weblink / Specs sheet](#)




LED POWER SUPPLY 350mA-DC / 8W
300 90 108
110-240V / 0|50-60Hz
Number of luminaires: 1

[Weblink / Specs sheet](#)




LED POWER SUPPLY 500mA-DC / 20W
300 90 92
110-240V / 0|50-60Hz
Number of luminaires: 2(1)

[Weblink / Specs sheet](#)




LED POWER SUPPLY 500mA-DC / 20W DIM8
300 90 117
220-240V / 50-60Hz
Number of luminaires: 2

[Weblink / Specs sheet](#)




LED POWER SUPPLY 500mA-DC / 32W DIM8
300 90 5120
110-240V / 50-60Hz
Number of luminaires: 2-2

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER
300 90 914
110-240V / 50-60Hz
Number of luminaires: 3 / 3 / - / -

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER DIM1
300 90 64
110-240V / 0|50-60Hz
Number of luminaires: 2 / 2(1) / - / -

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER DIM5
300 90 125
110-240V / 50-60Hz
Number of luminaires: 2 / 2(1)

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER DIM5
300 90 68
110-240V / 50-60Hz
Number of luminaires: 2 / 2(1) / - / -

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER DIM6
300 90 61
220-240V / 50-60Hz
Number of luminaires: 2 / 2(1) / -

[Weblink / Specs sheet](#)




LED POWER SUPPLY MULTI-POWER DIM7
300 90 124
110-240V / 50-60Hz
Number of luminaires: 2 / 2(1)

[Weblink / Specs sheet](#)



LED POWER SUPPLY MULTI-POWER DIM7
300 90 60
110-240V / 50-60Hz
Number of luminaires: 2 / 2(1) / -


[Weblink / Specs sheet](#)



LED POWER SUPPLY MULTI-POWER DIM9
300 90 63
110-240V / 0|50-60Hz
Number of luminaires: 3 / 3 / - / -

Related references
MOUNTING KITS

Weblink / Specs sheet



MOUNTING KIT R82 TRIMLESS O.F.A.
202 11 82 OFA